

| Мощность двигателя, кВт | Сечение токопроводящего провода, мм ² | | | | | | | | | | | | | | | | |
|-------------------------|--|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|
| | 1,5 | 2,5 | 4 | 6 | 10 | 16 | 25 | 35 | 50 | 70 | 95 | 120 | 150 | 185 | 240 | 300 | 400 |
| | Длина токопроводящего провода при условии падения напряжения на 2% | | | | | | | | | | | | | | | | |
| 1,1 | 141 | 234 | | | | | | | | | | | | | | | |
| 1,5 | 109 | 182 | 289 | | | | | | | | | | | | | | |
| 2,2 | 77 | 127 | 203 | | | | | | | | | | | | | | |
| 3 | 57 | 94 | 150 | 223 | | | | | | | | | | | | | |
| 4 | 44 | 74 | 117 | 175 | 289 | | | | | | | | | | | | |
| 5,5 | | 55 | 87 | 130 | 214 | 336 | | | | | | | | | | | |
| 7,5 | | 41 | 65 | 97 | 159 | 251 | | | | | | | | | | | |
| 11 | | | 44 | 66 | 109 | 172 | 263 | 360 | | | | | | | | | |
| 13 | | | | 56 | 92 | 145 | 222 | 303 | 416 | | | | | | | | |
| 17 | | | | 40 | 66 | 104 | 159 | 216 | 297 | | | | | | | | |
| 22 | | | | | 56 | 88 | 135 | 184 | 254 | 341 | | | | | | | |
| 32 | | | | | | 64 | 98 | 134 | 185 | 247 | 318 | | | | | | |
| 37 | | | | | | 54 | 85 | 116 | 160 | 215 | 277 | 339 | | | | | |
| 45 | | | | | | | 72 | 99 | 136 | 183 | 236 | 284 | | | | | |
| 55 | | | | | | | | 80 | 111 | 149 | 193 | 232 | 274 | | | | |
| 75 | | | | | | | | | 84 | 112 | 145 | 175 | 208 | 242 | 288 | | |
| 90 | | | | | | | | | | 88 | 113 | 136 | 160 | 185 | 219 | 250 | |
| 110 | | | | | | | | | | | 60 | 81 | 105 | 121 | 166 | 216 | 298 |
| 130 | | | | | | | | | | | | 78 | 99 | 115 | 136 | 178 | 248 |